

80A Mini AC/DC Clamp Meter

Small diameter elongated jaw

Designed for high resolution current measurements in hard to reach locations, this mini-clamp performs AC and DC low current tests where typical clamps cannot go.

Features:

- 4000 count LCD display
- 1mA resolution
- Jaw opens to 0.5" (12.7mm)
- AC/DC Voltage, Resistance, Frequency, Capacitance, and Duty Cycle
- Diode Test/Continuity Beeper
- Data Hold and Max Hold
- Complete with test leads, 9V battery and



Ordering Information:

38095080A Mini AC/DC Clamp Meter

| Specifications | Range | Resolution | Accuracy (%rdg+digits) |
|------------------|---------------------------------------|------------|------------------------|
| AC Current | 4A, 80A | 1mA | ±(2.5% + 5d) |
| DC Current | 4A, 80A | 1mA | ±(2.5% + 4d) |
| AC Voltage | 400mV to 600V | 0.1mV | ±(2.0% + 4d) |
| DC Voltage | 400mV to 600V | 0.1mV | ±(1.5% + 3d) |
| Resistance | 400Ω to 40MΩ | 0.1Ω | ±(1.5% + 2d) |
| Frequency | 5Hz to 10MHz | 0.001Hz | ±(1.2% + 3d) |
| Duty Cycle | 5 to 99.9% | 0.1% | ±(1.2% + 3d) |
| Dimension/Weight | 8.3x2.8x1.5" (210x70x37mm)/7oz (200g) | | |

