

AC/DC Mini Clamp Meter+Voltage Detector

Clamp meter with built-in AC Voltage detector + flashlight



Features:

- Measures 200A AC Current up to 100mA resolution
- 3% basic ACA accuracy
- 0.7" (18mm) jaw opening; 300MCM cable size
- 2000 count LCD display
- Non-contact AC Voltage detector (120/240VAC, 50/60Hz) via clamp tip
- Built-in white LED flashlight
- Measures Frequency up to 1kHz with 0.01Hz resolution
- Autoranging with Auto Power Off
- Data Hold
- Overload protection for all ranges
- Overrange and low battery indicators
- Complete with two AAA batteries

MA120 additional features

- 200A AC/DC Current
- Frequency measurement
- DCA zero key and backlit display



Bright LED Flashlight



Non-contact voltage detection via clamp tip

CE

Specifications	MA100	MA120
AC Current:	—	200A
DC Current:	—	200A
Max Resolution:	—	0.1A
Basic ACA Accuracy (%rdg):	—	±3%
AC Voltage (Max Res.):	—	Non-contact
Frequency (Max Res.):	—	1kHz (0.01Hz)
Dimensions:	6.5x2.6x1.3" (164x65x32mm)	
Weight:	6.2 oz (176g)	

Ordering Information:

- MA100**200A AC Mini Clamp Meter with Voltage Detector
MA100-NIST200A AC Mini Clamp Meter with Voltage Detector with NIST cert
MA120200A AC/DC Mini Clamp Meter with Voltage Detector
MA120-NIST200A AC/DC Mini Clamp Meter with Voltage Detector with NIST cert